



8-bit **AVR**<sup>®</sup>  
Microcontroller

Application  
Note

## AVR086: Replacing AT90S8535 by ATmega8535

### Features

- AT90S8535 Errata Corrected in ATmega8535
- Changes to Names
- Improvements to Timer/Counters and Prescalers
- Improvements to the ADC
- Improvements to SPI and UART
- Changes to EEPROM Write Timing
- Programming Interface
- Fuse Settings
- Oscillators and Selecting Start-up Delays
- Changes to Watchdog Timer
- Other Concerns
- Features not Available in AT90S8535 Compatibility Mode

### Introduction

This application note is a guide to assist current AT90S8535 users in converting existing designs to the ATmega8535. The ATmega8535 has two operating modes selected through the fuse settings. The S8515C Fuse selects whether the AT90S8535 compatibility mode should be used or not. By default, the S8515C Fuse is unprogrammed and the ATmega8535 does not operate in compatibility mode. When the compatibility mode is used, only non-conflicting enhancements make the part different from the AT90S8535. Additionally, the electrical characteristics of the ATmega8535 are different including an increase in operating frequency because of a change in process technology. Check the data sheet for detailed information. When the S8515C Fuse is unprogrammed, all new features are supported, but porting the code may require more work.

### AT90S8535 Errata Corrected in ATmega8535

The following items from the Errata Sheets of the AT90S8535 do not apply to the ATmega8535. Refer to the AT90S8535 Errata Sheet for a more detailed description of the errata.

Note: Some of these errata entries were corrected in the last revision of AT90S8535. They are still referred, to ease converting from any AT90S8535 design.

### Releasing Reset Condition Without Clock

ATmega8535 has a new reset interface in which any External Reset Pulse exceeding the minimum pulse width  $t_{RST}$  causes an internal reset even though the condition disappears before any valid clock is present.

Rev. 2520B-AVR-07/03





<b>Incorrect Channel Changes in Free Running Mode</b>	In ATmega8535, the MUXn and REFS1:0 bits in the ADMUX Register are buffered through a temporary register to which the CPU has random access. This ensures that the channels and reference selection only takes place at a safe point during the conversion. Refer to the ATmega8535 data sheet for further information and advices on how to change these registers in Free Running mode.
<b>32 kHz Oscillator May Fail at Higher Voltages</b>	In ATmega8535, the 32 kHz crystal Oscillator for Timer/Counter2 also works above 4.0V. Refer to the ATmega8535 data sheet for electrical characteristics.
<b>Incorrect Start-up Time</b>	The FSTRT Fuse in AT90S8535 is replaced by a more flexible system in ATmega8535, in which the fuses CKSEL3:0 and SUT1:0 selects clock source, frequency range, and Start-up times. Refer to the ATmega8535 data sheet for further information
<b>Lock Bits at High <math>V_{CC}</math> and Temperature</b>	In ATmega8535, the Lock bits can be cleared over the full operating range.
<b>Error in Half Carry Flag</b>	The Half Carry Flag works as expected in ATmega8535.
<b>Error in Writing Reset Status Bits</b>	The POR and XTRF Flag can be cleared individually in ATmega8535.
<b>Wake-up from Sleep Executes Instructions before Interrupt is Serviced</b>	ATmega8535 executes the Interrupt routine as the first instruction after wake-up from Power-save mode.  If an enabled interrupt occurs while the ATmega8535 is in a sleep mode, the MCU wakes up. The MCU is then halted for four cycles, executes the interrupt routine, and resumes execution from the instruction following SLEEP.
<b>SPI Can Send Wrong Byte</b>	In ATmega8535, a new byte can be written to the SPI Data Register on the same clock edge as the previous transfer finishes. There is no need to wait for the previous transfer to complete before writing the next byte into the SPI Data Register when operating in Master mode.
<b>Output Compare Output Value Corrupted by Writing to Port</b>	When OC1A and/or OC1B are used, writing to PORTD I/O location does not disturb the operation of the compare pins.
<b>Serial Programming at Voltages Below 3.4V</b>	There are no restrictions on the supply voltage or system frequency as long as the device is operated inside the voltage and frequency range prescribed in the data sheet for the ATmega8535.
<b>Wake-up from Power-save without Global Interrupt Enable</b>	Asynchronous Timer/Counter interrupts do not wake-up the part unless global interrupts are enabled in ATmega8535
<b>UART Looses Synchronization if RXD Line is Low when UART Receive is Disabled</b>	The UART is replaced with a USART, which does not have this problem. The starting edge of a reception is only accepted as valid if the Receive Enable bit in the USART Control Register is set.
<b>High Current Consumption at High <math>V_{CC}</math></b>	ATmega8535 has the electrical characteristics described in its data sheet.
<b>Leakage Current on Tri-stated I/O Pins</b>	ATmega8535 has the electrical characteristics described in its data sheet.

## Changes to Names

The following control bits have changed names, but have the same functionality and placement when accessed as in AT90S8535:

**Table 1.** Changed Bit Names

Bit Name in AT90S8535	Bit Name in ATmega8535	I/O Register (AT90S8535)	Comments
PWMn(0)	WGMn0	TCCRn(A)	"A" and "0" in 16-bit Timer only.
PWMn1	WGMn1	TCCRnA	
CTCn	WGMn2	TCCRn(B)	"B" in 16-bit Timer only
WDTOE	WDCE	WDTCR	See "Changes to Watchdog Timer" on page 9.
CHR9	UCSZ2	UCR	
OR	DOR	USR	

The following I/O Registers have changed names, but include the same functionality and placement when accessed as in AT90S8535:

**Table 2.** Changed Register Names

Register Name in AT90S8535	Register Name in ATmega8535	Comments
GIMSK	GICR	
MCUSR	MCUCSR	
UBRR	UBRRL	
USR	UCSRA	
UCR	UCSRB	
ADCSR	ADCSRA	

## Improvements to Timer/Counters and Prescalers

For details about the improved and additional features, please refer to the data sheet. The following features have been added:

- The Prescalers in ATmega8535 can be reset.
- Variable top value in PWM mode.
- For Timer/Counter1, Phase and Frequency Correct PWM mode in addition to the Phase Correct PWM mode.
- Fast PWM mode.
- Timer0 extended with PWM and Output Compare function.

## Differences Between ATmega8535 and AT90S8535

Most of the improvements and changes apply to all the Timer/Counters and the description below is written in a general form. A lower case “x” replaces the output channel (A or B for Timer/Counter1, N/A for Timer/Counter0 and Timer/Counter2), while “n” replaces the Timer/Counter number (n = 0, 1, or 2).

### TCNT1 Cleared in PWM Mode

In AT90S8535 there are three different PWM resolutions – 8, 9, or 10 bits. Though only 8, 9, or 10 bits are compared, it is still possible to write values into the TCNT1 Register that exceed the resolution. Thus, the Timer/Counter has to complete the count to 0xFFFF before the reduced resolution becomes effective (i.e, if 8-bit resolution is selected and the TCNT1 Register contains 0x0100, the top value (0x00FF) will not be effective until the counter has counted up to 0xFFF, turned, and counted down to 0x0000 again). In ATmega8535 this has been changed so that the unused bits in TCNT1 are being cleared to zero to avoid this unintended counting up to 0xFFFF. In the ATmega8535, the TCNT1 Register never exceeds the selected resolution.

*ATmega8535*

The most significant bits in the TCNT1 Register will be cleared at the first positive edge of the prescaled clock.

- 8-bit PWM: TCNT1H7:0 = 0
- 9-bit PWM: TCNT1H7:1 = 0
- 10-bit PWM: TCNT1H7:2 = 0

*AT90S8535*

TCNT1H not cleared.

### OCR1xH Cleared in PWM Mode

Clearing OCR1xH in PWM mode is slightly different from clearing TCNT1. The AT90S8535 clears the six most significant bits if 8, 9, or 10 bits PWM mode is selected. Hence, if 0xFFFF is written to OCR1x in PWM-mode and OCR1x is read back, the result is 0x03FF regardless of which PWM mode that is selected. In ATmega8535 the number of cleared bits depends on the resolution.

*ATmega8535*

The most significant bits in OCR1AH and OCR1BH are cleared when they are updated at the TOP-value of the counter.

- 8-bit PWM: OCR1xH7:0 = 0
- 9-bit PWM: OCR1xH7:1 = 0
- 10-bit PWM: OCR1xH7:2 = 0

*AT90S8535*

The six most significant bits in the OCR1AH and OCR1BH are cleared regardless of the resolution.



**Write to OCR1x in PWM Mode, Change to Normal Mode Before OCR1x is Updated at the Top, Read OCR1x**

As described in the data sheet, the OCR1x Registers are updated at the top value when written. Thus, when writing the OCR1x in PWM mode, the value is stored in a temporary buffer. When the Timer/Counter reaches the top, the temporary buffer is transferred to the actual Output Compare Register. If PWM mode is left after the temporary buffer is written, but before the actual Output Compare Register is updated, the behavior differs between ATmega8535 and AT90S8535.

*ATmega8535*

If the OCR1x Register is read before the update is done, the actual compare value is read – not the temporary OCR1x buffer.

*AT90S8535*

If the OCR1x Register is read before the update is done, the value in the OCR1x buffer is read. For example, the value read is the one last written (to the OCR1x buffer), but since the Timer/Counter never reached the top value, it was not latched into the OCR1x Register. Hence, the value that is used for comparison is not necessarily the same as being read.

Note: This applies to 16-bit Timer/Counter only, for 8-bit Timer/Counter, the temporary buffer is read in both devices.

**Memory of Previous OCnx pin Level**

In AT90S8535, there are two settings of COMnx1:0 that do not update the OCnx pin in PWM mode (0b00 and 0b01), and one setting of COMnx1:0 in non-PWM mode (0b00). Assume the Timer/Counter is taken from a state that updates the OCnx pin to a state that does not, and then back again to a state that does update the OCnx pin. The following differences should be noted:

*ATmega8535*

The level of the OCnx-pin before disabling the Output Compare mode is remembered. Re-enabling the Output Compare mode will cause the OCnx pin to resume operation from the state it had when it was disabled. All Output Compare pins are initialized to zero on Reset.

*AT90S8535*

For Timer/Counter1 in non-PWM mode, a compare match during the time when the Timer/Counter is not connected to the pin will reset the OCnx pin to the low level once enabled again. PWM mode will update the internal register for the OCnx pin, such that the state of the pin is unknown once enabled again.

**Improvements to ADC**

- ATmega8535 supports both left adjusted and right adjusted 10-bit results.
- The ADC in ATmega8535 supports differential and amplified measurements.
- ATmega8535 supports ADC conversion start on auto-triggering on interrupt sources.

## Improvements to SPI and USART

Both SPI and USART have new Double Speed modes which allow higher communication speed.

The UART in AT90S8535 has been replaced by a USART in ATmega8535. The ATmega8535 USART is compatible with the AT90S8535 UART with one exception: The two-level Receive Register acts as a FIFO. The FIFO is disabled when the S8515C Fuse is programmed. Still the following must be kept in mind when the S8515C Fuse is programmed:

- The UDR must only be read once for each incoming data.
- The Error Flags (FE and DOR) and the ninth data bit (RXB8) are buffered with the data in the receive buffer. Therefore the status bits must always be read before the UDR Register is read. Otherwise, the error status will be lost.

Another minor difference is the initial value of RXB8, which is “1” in the UART in AT90S8535 and “0” in the USART in ATmega8535

## Changes to EEPROM Write Timing

In AT90S8535, the EEPROM write time is dependent on supply voltage, typically 2.5 ms @  $V_{CC} = 5V$  and 4 ms @  $V_{CC} = 2.7V$ . In ATmega8535, the EEPROM write time takes 8,448 cycles of the calibrated RC Oscillator (regardless of the clock source and frequency for the system clock). The calibrated RC Oscillator is assumed to be calibrated to 1.0 MHz regardless of  $V_{CC}$ , i.e., typical write time is 8.4 ms.

Note: Changing the value in the OSCCAL Register affects the frequency of the calibrated RC Oscillator and hence the EEPROM write time.

## Programming Interface

Some changes have been done to the programming interface, especially in the In-System Programming interface. This has been done to support all the additional fuses in ATmega8535. The timing requirements are unchanged. See the ATmega8535 data sheet for details.

The Parallel Programming algorithm is changed. The most significant change is the introduction of the PAGEL pin on PD7, and the BS2 pin on PA0. This extension is needed to support page programming of Flash, EEPROM and additional fuses in ATmega8535. Note that the additional fuses and Lock bits also require a change in the fuse writing algorithm. The timing requirements for parallel programming have been changed. See the ATmega8535 data sheet for details.

The STK500 supports both In-System Programming and Parallel Programming of the ATmega8535.

## Fuse Settings

ATmega8535 contains more fuses than AT90S8535. Table 3 shows the AT90S8535 compatible fuse settings. Some of the fuses are described further in the following sections.

**Table 3.** Comparing Fuses in AT90S8535 and ATmega8535<sup>(1)</sup>

Fuse	Default AT90S8535 Setting	Default ATmega8535 Setting	AT90S8535 Compatible Setting
S8515C	–	1	0
WDTON	–	1	1
SPIEN	0	0	0
CKOPT	–	1	0 <sup>(2)</sup>
EESAVE	–	1	1
BOOTSZ1	–	0	0 (N/A) <sup>(3)</sup>
BOOTSZ0	–	0	0 (N/A) <sup>(3)</sup>
BOOTRST	–	1	1
BODLEVEL	–	1	1
BODEN	–	1	1
SUT1	–	1	See note <sup>(4)</sup>
SUT0	–	0	See note <sup>(4)</sup>
CKSEL3	–	0	See note <sup>(4)</sup>
CKSEL2	–	0	See note <sup>(4)</sup>
CKSEL1	–	0	See note <sup>(4)</sup>
CKSEL0	–	1	See note <sup>(4)</sup>

- Notes:
1. A dash indicates that the fuse is not present in AT90S8535.
  2. See “Oscillators and Selecting Start-up Delays” on page 8.
  3. SPM and Self-Programming is not available in AT90S8535. The default factory setting of BOOTSZ1:0 is OK when porting the design to ATmega8535.
  4. The SUT Fuses in ATmega8535 replaces the FSTRT fuse in AT90S8535. The SUT and CKSEL setting must be considered when moving to ATmega8535. See “Oscillators and Selecting Start-up Delays” on page 8.

## Oscillators and Selecting Start-up Delays

ATmega8535 provides more Oscillators and Start-up time selections than AT90S8535. During wake-up from Power-down mode, the ATmega8535 uses the CPU frequency to determine the duration of the wake-up delay, while AT90S8535 determines the delay from the WDT Oscillator frequency.

Follow the guidelines from the section “System Clock and Clock Options” in the ATmega8535 data sheet to find appropriate start-up values.

Special attention must be paid when changing the fuses in In-System Programming mode. In-System Programming is dependent on a system clock. If wrong Oscillator setting is programmed, it may be impossible to re-enter In-System Programming mode due to missing system clock (Parallel Programming mode must then be used).

The crystal oscillator in AT90S8535 is capable of driving an addition clock buffer from the XTAL2 output. In ATmega8535, this is only possible when the CKOPT Fuse is programmed. In this mode the Oscillator has a rail-to-rail swing at the output, but at the expense of higher power consumption. Hence, do only program this fuse when rail-to-rail swing is required.

## Changes to Watchdog Timer

The Watchdog Timer in ATmega8535 is improved compared to the one in AT90S8535. In AT90S8535, the Watchdog Timer is either enabled or disabled, while ATmega8535 supports two safety levels selected by the WDTON Fuse. See description in ATmega8535 data sheet for further information.

The combination of programming the S8515C Fuse and having the WDTON Fuse unprogrammed makes the Watchdog Timer behave exactly as in AT90S8535.

The frequency of the Watchdog Oscillator in ATmega8535 is close to 1.0 MHz for all supply voltages. The typical frequency of the Watchdog Oscillator in AT90S8535 is close to 1.0 MHz at 5V, but the Time-out period increases with decreasing  $V_{CC}$ . This means that the selection of Time-out period for the Watchdog Timer (in terms of number of WDT Oscillator cycles) must be reconsidered when porting the design to ATmega8535. Refer to the data sheet for ATmega8535 for further information.

## Other Concerns

The ATmega8535 has a Signature Byte different from the one used in AT90S8535. Make sure you are using the Signature Byte of ATmega8535 when porting the design.

Be aware that EEPROM write access must be completed before entering power-down sleep mode. Otherwise the system oscillator will continue to run, drawing additional current.

## Features not Available in AT90S8535 Compatibility Mode

The cS8515C Fuse makes the ATmega8535 compatible to AT90S8535. However, with the S8515C Fuse programmed, some of the new features in ATmega8535 become unavailable. The following features are not supported when the ATmega8535 is used in the AT90S8535 compatibility mode:

- The FIFO operation of the USART.
- Access to the status bits WDRF and BORF in MCUCSR.
- A timed sequence to change Watchdog Timer prescaler settings by software.
- External Interrupt INT2. The INT2 bit in the General Interrupt Control Register – GICR – cannot be written to one, and the INT2 bit in General Interrupt Flag Register – GIRF – will always read as zero.
- Compare function of Timer/Counter0. The OCIE0 bit in the Timer Interrupt Mask Register – TIMSK – cannot be written to one, and the OCIF0 bit in the Timer Interrupt Flag Register – TIFR – will always read as zero.

If any of the features above are needed or wanted and the S8515C Fuse is unprogrammed, this introduces some differences between ATmega8535 and AT90S8535 which do not exist as long as the compatibility fuse is programmed:

- A timed sequence must be followed to change Watchdog Timer prescaler settings by software.
- In the MCUCSR Register, all RESET Flags are present in the register, not only EXTRF and PORF as in AT90S8535.
- The UART will have an extra input buffer which allows one more data byte to be received before the Data OverRun Flag (DOR) is set.



## Atmel Corporation

2325 Orchard Parkway  
San Jose, CA 95131  
Tel: 1(408) 441-0311  
Fax: 1(408) 487-2600

## Regional Headquarters

### Europe

Atmel Sarl  
Route des Arsenalux 41  
Case Postale 80  
CH-1705 Fribourg  
Switzerland  
Tel: (41) 26-426-5555  
Fax: (41) 26-426-5500

### Asia

Room 1219  
Chinachem Golden Plaza  
77 Mody Road Tsimshatsui  
East Kowloon  
Hong Kong  
Tel: (852) 2721-9778  
Fax: (852) 2722-1369

### Japan

9F, Tonetsu Shinkawa Bldg.  
1-24-8 Shinkawa  
Chuo-ku, Tokyo 104-0033  
Japan  
Tel: (81) 3-3523-3551  
Fax: (81) 3-3523-7581

## Atmel Operations

### Memory

2325 Orchard Parkway  
San Jose, CA 95131  
Tel: 1(408) 441-0311  
Fax: 1(408) 436-4314

### Microcontrollers

2325 Orchard Parkway  
San Jose, CA 95131  
Tel: 1(408) 441-0311  
Fax: 1(408) 436-4314

La Chantrerie  
BP 70602  
44306 Nantes Cedex 3, France  
Tel: (33) 2-40-18-18-18  
Fax: (33) 2-40-18-19-60

### ASIC/ASSP/Smart Cards

Zone Industrielle  
13106 Rousset Cedex, France  
Tel: (33) 4-42-53-60-00  
Fax: (33) 4-42-53-60-01

1150 East Cheyenne Mtn. Blvd.  
Colorado Springs, CO 80906  
Tel: 1(719) 576-3300  
Fax: 1(719) 540-1759

Scottish Enterprise Technology Park  
Maxwell Building  
East Kilbride G75 0QR, Scotland  
Tel: (44) 1355-803-000  
Fax: (44) 1355-242-743

### RF/Automotive

Theresienstrasse 2  
Postfach 3535  
74025 Heilbronn, Germany  
Tel: (49) 71-31-67-0  
Fax: (49) 71-31-67-2340

1150 East Cheyenne Mtn. Blvd.  
Colorado Springs, CO 80906  
Tel: 1(719) 576-3300  
Fax: 1(719) 540-1759

### Biometrics/Imaging/Hi-Rel MPU/ High Speed Converters/RF Datacom

Avenue de Rochepleine  
BP 123  
38521 Saint-Egreve Cedex, France  
Tel: (33) 4-76-58-30-00  
Fax: (33) 4-76-58-34-80

---

### e-mail

[literature@atmel.com](mailto:literature@atmel.com)

### Web Site

<http://www.atmel.com>

**Disclaimer:** Atmel Corporation makes no warranty for the use of its products, other than those expressly contained in the Company's standard warranty which is detailed in Atmel's Terms and Conditions located on the Company's web site. The Company assumes no responsibility for any errors which may appear in this document, reserves the right to change devices or specifications detailed herein at any time without notice, and does not make any commitment to update the information contained herein. No licenses to patents or other intellectual property of Atmel are granted by the Company in connection with the sale of Atmel products, expressly or by implication. Atmel's products are not authorized for use as critical components in life support devices or systems.

© Atmel Corporation 2003. All rights reserved. Atmel® and combinations thereof, AVR® and AVR Studio® are the registered trademarks of Atmel Corporation or its subsidiaries.

Other terms and product names may be the trademarks of others.



Printed on recycled paper.